

Movement sensor
module
BMM 611-0 SM
200017198-03

Product description

Movement sensor module for Siedle Vario with photoelectric lighting controller and a horizontal pick-up angle of max. 180°.

Passive infrared detectors (PIR detectors) respond to changes in the incident infrared radiation. To detect motion, the moving object must radiate heat itself.

- Pick-up angle/pick-up width can be changed via aperture insert
- Photoelectric lighting controller range can be adjusted
- Switch-off delay can be set
- Photoelectric lighting controller and movement sensor module can be used individually or combined

Specifications

| | |
|----------------------------|-------------------|
| Operating voltage: | 12 V AC |
| Operating current: | max. 120 mA |
| Contact type: | contact 24 V, 2 A |
| Switching time: | 5 sec to 15 min |
| Protection system: | IP 54 |
| Ambient temperature: | -20 °C to +55 °C |
| Height of structure (mm): | 25 |
| Dimensions (mm) W x H x D: | 99 x 99 x 51 |


Article information

| Article designation | Article description | Colour/Material | KG SAP article no. |
|---------------------|------------------------|-----------------|--------------------|
| BMM 611-0 SM | Movement sensor module | Silver metallic | B 200017198-03 |

Accessories

| Article designation | Article description | Colour/Material | KG | SAP article no. |
|---------------------|---------------------|-----------------|----|-----------------|
| Vario 611 SM | Touch-up applicator | Silver metallic | 0 | 210007117-00 |

Spare parts



Movement sensor
module
BMM 611-0 SM

200317198


Page 2


| Article designation | Article description | Colour/Material | KG | SAP article no. |
|---------------------|---------------------------------------|-----------------|----|-----------------|
| BMM 611-... | Replacement panel for range reduction | Translucent | E | 200031327-00 |
| BMM 611-... | Terminal block | Black | E | 200029976-00 |
| BMM 611-... SM | Screen frame | Silver metallic | E | 210006023-00 |

Movement sensor
module
BMM 611-0 SM

200317198

Page 3





Movement sensor
module
BMM 611-0 SM

200317198

Page 4

BMM 611-0 Movement sensor module

Product information

889 kB

[Download](#)

Declaration of Conformity

4,4 MB

[Download](#)

Additional information

140 kB

[Download](#)